

# GRAS 43AG

Ear & Cheek Simulator



Dyn range: 25 dB(A) to 164 dB  
or 10.5 dB(A) to 113 dB (low-noise version)  
ANSI: S3.7  
IEC: 60318-4

---

The GRAS 43AG Ear and Cheek Simulator represents the section of a head important for realistic reproduction of the acoustic properties of the ear of an average human head. It allows the use of an ITU-T type 3.3 pinna or an Anthropometric Pinna, either with an IEC 60318-4 Ear Simulator, a Low-noise Ear Simulator system or a High Resolution Ear Simulator.

## Introduction

The GRAS 43AG Ear and Cheek Simulator is a unique, multi-faceted and multi-purpose tool that helps you accomplish the job in an effective and efficient manner. We call it the table-top KEMAR as it offers you much of the KEMAR capability in a convenient and portable packaging.

Our vision for the 43AG is to assist you in all facets of the product development cycle: From R&D testing to the final test and approval of the finished product. As your product is put together, your team needs to ensure that individual changes do not conflict with your overall vision. Much of this validation work can be accomplished at their desks, in real time, making you comfortable and giving you the stamp of approval of the final product.

Additionally, very few manufacturers have their entire production vertically integrated and are therefore highly dependent on the quality delivered by their sub-suppliers. To ensure the quality of the complete product, GRAS offers a variety of mobile test platforms that can easily be deployed at your supplier and in your own in-coming control department. The 43AG Ear and Cheek Simulator by GRAS provides that comfort and security: The parts comply to the highest standards: Yours.

## Typical applications and use

The 43AG is a multi-purpose tool and can for example be used to verify frequency response, distortion, isolation and leakage.

Its versatility means that it can be used for testing of both concha and insert types earphones. It can also be used for headphone and headset testing, both circumaural and supra-aural types. Also, all common types of hearing-aids, and telephone handset can be tested with the 43AG.

To make ordering and decision making easier, we

have made 43AG available in a number of configurations. Except for a few simple steps, they are fully assembled, calibrated and ready for use.

The following configurations are available:

### 43AG-1 and -2

*43AG-1 Ear and Cheek Simulator LEMO* is configured with an Externally Polarized Ear Simulator According to IEC 60318-4 and a large KEMAR Right Pinna 55 Shore 00.

*43AG-2 Ear and Cheek Simulator CCP* is configured with a Prepolarized Ear Simulator According to IEC 60318-4 and a large KEMAR Right Pinna 55 Shore 00.

With these configurations, tests can be performed according to the following standards:

- IEC 60959
- IEC 60318-4 (former IEC 60711)
- ITU-T Rec. P.57 Type 2 Artificial Ear
- ITU-T Rec. P.57 Type 3.3 Pinna Simulator

### 43AG-3 and -4

*43AG-3 Ear and Cheek Simulator w Anthropometric Pinna LEMO* is configured with an Externally Polarized Ear Simulator According to IEC 60318-4 and a large KEMAR Right Anthropometric Pinna 35 Shore 00.

*43AG-4 Ear and Cheek Simulator w Anthropometric Pinna CCP* is configured with a Prepolarized Ear Simulator According to IEC 60318-4 and a large KEMAR Right Anthropometric Pinna 35 Shore 00.

The anthropometric pinna has anatomically shaped concha and ear canal, resulting in Improved fit and repeatability. The outer pinna has improved collapsibility. In addition to the traditional push

mounting from the outside, the pinna is secured with two screws from the inside. These two screws ensure that the pinna is held firmly in place. Therefore, it seals perfectly against the ear simulator and the cheek plate, and it is therefore possible to mount and dismount DUTs repeatedly without compromising the seal. The outer shape of the anthropometric pinna conforms with ITU-T Type 3.3. Read more about the anthropometric pinna [here](#).

Choose one of these configurations if you need to test insert type earphones, or if you want the benefits of the improved collapsibility of the new pinna when testing circum- and supra-aural earphones.

## 43AG-5

*43AG-5 Ear and Cheek Simulator, Low-noise*, is configured with a 43BB low-noise ear simulator system and a large KEMAR Right Anthropometric Pinna 35 Shore 00.

The anthropometric pinna has anatomically shaped concha and ear canal and offers better fit, placement and seal, resulting in improved low frequency testing and better low-noise testing. Also, the more realistic ear canal combined with a more flexible pinna provides greater repeatability in measurements of in-ear, circum-aural or supra-aural headphones. The outer shape of the anthropometric pinna conforms with ITU-T Type 3.3. Read more about the advantages of the anthropometric pinna [here](#).

The reduced noise floor of the 43BB low-noise system results in very good correlation to subjective listening results. Read more about the 43BB Low-noise Ear Simulator System [here](#).

## 43AG-6 and -7

*43AG-6 Ear and Cheek Simulator, High Resolution*,

*LEMO* is configured with an externally polarized High Resolution Ear Simulator and a large KEMAR Right Anthropometric Pinna 35 Shore 00.

*43AG-7 Ear and Cheek Simulator, High Resolution CCP* is configured with a prepolarized High Resolution Ear Simulator and a large KEMAR Right Anthropometric Pinna 35 Shore 00.

The GRAS RA0401 is an externally polarized high resolution version of the well-known standardized 60318-4 ear simulator, RA0402 is the prepolarized equivalent. They comply with IEC60318-4, but extend the useful frequency range to 20 kHz within a narrow tolerance band. Read more about the RA0401 [here](#), and the RA0402 [here](#).

The anthropometric pinna has anatomically shaped concha and ear canal and offers better fit, placement and seal, resulting in improved low and high frequency testing. Also, the more realistic ear canal combined with a more flexible pinna provides greater repeatability in measurements of in-ear, circum-aural or supra-aural headphones. The outer shape of the anthropometric pinna conforms with ITU-T Type 3.3. Read more about the advantages of the anthropometric pinna [here](#).

----

The contents of each of these configurations are listed in the tab Ordering info.

## Compatibility

KEMAR pinnae are available for the 43AG: small and large in "soft" and "normal" versions. VA-Style as well as anthropometric pinnae are available. To ensure that the base of the pinna is flush with the cheek plate, only right pinnae should be used.

## System verification

For sensitivity calibration, we recommend using a

pistonphone like GRAS 42AP Intelligent Pistonphone or the GRAS 42AA Pistonphone.

## Quality and warranty

All GRAS microphones are made of high-quality materials that will ensure life-long stability and robustness. The microphones are all assembled in verified clean-room environments by skilled and dedicated operators with many years of expertise in this field.

The microphone diaphragm, body, and improved protection grid are made of high-grade stainless steel, which makes the microphone resistant to physical damage, as well as corrosion caused by aggressive air or gasses.

This, combined with the reinforced gold-plated microphone terminal which guarantees a highly reliable connection, enables GRAS to offer 5 years warranty against defective materials and workmanship.

## Service

If you accidentally damage the diaphragm on a GRAS microphone, we can – in most cases – replace it at a very reasonable cost and with a short turn-around time. This not only protects your investment, but also pleases your quality assurance department because you don't have to worry about new serial numbers, etc.

## Calibration

Before leaving the factory, all GRAS microphones are calibrated in a controlled laboratory environment using traceable calibration equipment.

Depending on the use, measurement environment, and internal quality control programs, we recommend recalibrating the microphone at least once a year.

Theoretical dynamic range lower limit with GRAS preamplifier	dB(A)	25
Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / ±14 V power supply	dB	153
Theoretical dynamic range upper limit with GRAS preamplifier @ +120 V / ±60 V power supply	dB	164
Set sensitivity @ 250 Hz (±2 dB)	mV/Pa	12.5
Set sensitivity @ 250 Hz (±2 dB)	dB re 1V/Pa	-38.1
Coupler volume	mm <sup>3</sup>	1260 @ 500 Hz
Resonance frequency	kHz	13.5 (ear sim)
Temperature range, operation	°C / °F	-30 to 60 / -22 to 140
Temperature coefficient @250 Hz	dB/°C / dB/°F	- 0.01 / -0.006
Humidity range non condensing	% RH	0 to 75
ANSI standard		S3.7
IEC standard		60318-4 (former 60711)
ITU-T recommendations		P.380
CE/RoHS compliant/WEEE registered		Yes/Yes/Yes
Weight	g / oz	1.95 kg / 68.784

Specifications are valid for 43AG-1 to 4 and 6 to 7. The specifications for the GRAS 43BB Low-noise Ear Simulator System used in 43AG-5 can be found at the product page for 43BB at GRAS.dk.

GRAS Sound & Vibration reserves the right to change specifications without notice.

## Included

### 43AG-1 Ear and Cheek Simulator LEMO

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB0065</a>	KEMAR Large Right Pinna 55 Shore 00
GRAS GR0917	Ear Canal Extension
<a href="#">GRAS RA0045</a>	Externally polarized Ear Simulator According to IEC 60318-4
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26AC</a>	1/4" Preamplifier with 3 m integrated cable
GRAS RA0199	Finger Simulator
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

### 43AG-2 Ear and Cheek Simulator CCP

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB0065</a>	KEMAR Large Right Pinna 55 Shore 00
GRAS GR0917	Ear Canal Extension
<a href="#">GRAS RA0045-S1</a>	Prepolarized Ear Simulator According to IEC 60318-4
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26CB</a>	1/4" Preamplifier
<a href="#">GRAS AA0070</a>	Microdot to BNC Cable, 3 m
GRAS RA0199	Finger Simulator
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

## 43AG-3 Ear and Cheek Simulator w Anthropometric Ear LEMO

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB5000</a>	KEMAR Large Right Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder
GRAS SK6012	Finger Screw, 2 pcs
<a href="#">GRAS RA0045</a>	Externally Polarized Ear Simulator According to IEC 60318-4
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26CA</a>	1/4" Preamplifier with 3 m integrated cable
GRAS RA0199	Finger Simulator
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

## 43AG-4 Ear and Cheek Simulator w Anthropometric Ear CCP

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB5000</a>	KEMAR Large Right Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder
GRAS SK6012	Finger Screw, 2pcs
<a href="#">GRAS RA0045-S1</a>	Pre-polarized Ear Simulator According to IEC 60318-4
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26CB</a>	1/4" Preamplifier
<a href="#">GRAS AA0070</a>	Microdot to BNC Cable, 3 m
GRAS RA0199	Finger Simulator

GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

## 43AG-5 Ear and Cheek Simulator, Low-noise

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB5000</a>	Large Right Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder
GRAS SK6012	Finger Screw, 2 pcs
<a href="#">GRAS RA0001</a>	Right Angled 1/2" to 1/4" Adapter
<a href="#">GRAS RA0234</a>	Low-noise Ear Simulator
<a href="#">GRAS 26HG</a>	1/4" Preamp, High Impedance
GRAS 26HT	Filter and Gain Unit
GRAS AA0059	LEMO 7-pin to 7-pin cable, 1 m
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut
GRAS RA0199	Finger Simulator
<a href="#">GRAS 12HF</a>	Power Module for Low-noise Systems

## 43AG-6 Ear and Cheek Simulator w High Resolution Ear Simulator, LEMO

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB5000</a>	KEMAR Large Right Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder
GRAS SK6012	Finger screw for pinna, 2pcs



<a href="#">GRAS RA0401</a>	Externally Polarized High Resolution Ear Simulator
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26AC</a>	1/4" Preamplifier with 3 m integrated cable
GRAS RA0199	Finger Simulator
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

## 43AG-7 Ear and Cheek Simulator w High Resolution Ear Simulator, CCP

<a href="#">GRAS RA0052</a>	Test Jig with mounting base and adjustable force clamp
GRAS RA0314	Cheek plate
<a href="#">GRAS KB5000</a>	KEMAR Large Right Anthropometric Pinna 35 Shore 00
GRAS GR1874	Ear Simulator Holder
GRAS SK6012	Finger Screw, 2pcs
<a href="#">GRAS RA0402</a>	Pre-polarized High Resolution Ear Simulator
<a href="#">GRAS RA0001</a>	Right-angled 1/2" to 1/4" Adapter
<a href="#">GRAS 26CB</a>	1/4" Preamplifier
<a href="#">GRAS AA0070</a>	Microdot to BNC Cable, 3 m
GRAS RA0199	Finger Simulator
GRAS GR0408	External Ear Canal
GRAS GR0409	Union Nut

## Optional

### Power Supply & Signal Conditioning

<a href="#">GRAS 12AQ</a>	For both externally and prepolarized configurations: Power Module, dual-channel
<a href="#">GRAS 12AK</a>	For externally polarized configurations, Power Module, single-channel

[GRAS 12AU](#)

1-Channel Power Module with Signal Conditioning and Power Amplifier

## Pinna Simulators

<a href="#">GRAS KB0060</a>	KEMAR Small Right Pinna 55 Shore 00
<a href="#">GRAS KB0065</a>	KEMAR Large Right Pinna 55 Shore 00
<a href="#">GRAS KB1060</a>	KEMAR Small Right Pinna 35 Shore 00
<a href="#">GRAS KB1065</a>	KEMAR Large Right Pinna 35 Shore 00
<a href="#">GRAS KB0090</a>	KEMAR Large Right Pinna (VA-Style/SQ) 55 Shore 00
<a href="#">GRAS KB1090</a>	KEMAR Large Right Pinna (VA-Style) 35 Shore 00

## Calibration Equipment

<a href="#">GRAS RA0184</a>	Force Gauge (0 - 25 N)
<a href="#">GRAS RA0157</a>	1/2" Calibration Adapter for KEMAR pinnae (required for an 60318-4 (711) Configuration)
<a href="#">GRAS 42AP</a>	Pistonphone with built-in precision barometer (250 Hz or 251.2 Hz, 114 dB $\pm$ 0.05 dB) (recommended)
<a href="#">GRAS 42AA</a>	Pistonphone (250 Hz, 114 dB $\pm$ 0.08 dB)
<a href="#">GRAS RA0090</a>	94 dB Pistonphone Coupler for calibration of low-noise system

## Cables

<a href="#">GRAS AA0008</a>	3 m Extension cable, 7-pin LEMO to 7-pin LEMO for connection to power module
-----------------------------	--

## Miscellaneous

<a href="#">GRAS RA0196</a>	High-tension Spring Kit (only relevant for 43AG delivered before summer 2014 and only if higher tension is required).
-----------------------------	---

GRAS Sound & Vibration reserves the right to change accessories without notice.

# | We Make Microphones

## Tradition

Since the establishment in 1994, GRAS has been 100% dedicated to developing and manufacturing high-quality measurement microphones and related acoustic equipment.

## Innovation

We work with everybody with an interest in sound or noise within the fields of aerospace, automotive, audiology, consumer electronics, noise monitoring, building acoustics and telecommunications.

## Quality

At GRAS we know that in order for you to trust your measurement results; signal quality, stability and robustness are essentials. We design and build them to perform under real life conditions – and beyond.

