

GRAS 12AR

2-Channel Power Module



Connection: Traditional 200 V
Channel(s): 2

The GRAS 12AR Power Module is a dual-channel power supply for preamplifiers used with condenser microphones. It is for general use in acoustic measurements; both in the laboratory and in the field.

Typical Applications and Use

- General-purpose measurements
- Two channels
- Precision measurements
- Acoustic monitoring
- Microphone calibration
- 0 V or 200 V polarization

Design

The 12AR can be powered either by internal standard batteries or an external DC supply (4.5 V-24 V), e.g. a mains/line adapter. It is built into a sturdy anodized aluminum cabinet.

The polarization voltage for the microphones fitted to the preamplifiers can be set to 0 V – for prepolarized microphones, or 200 V – for externally polarized microphones.

The 12AR also supplies ± 15 V to power the preamplifiers. It will run for approximately 30 hours on fresh standard alkaline batteries. A Low Batt LED indicates the condition of the batteries.

The inputs are two 7-pin LEMO sockets on the front panel, which are wired up for GRAS microphone preamplifiers, e.g. 26AB, 26AC, 26AJ, and 26AK, but is also compatible with other available makes of similar microphone preamplifiers.

The signals from the preamplifiers are AC coupled to the outputs which are standard BNC sockets also on the front panel.

Warranty

All GRAS products are made of high-quality materials that will ensure life-long stability and robustness. The 12AR is delivered with a 2-year warranty. The warranty does not cover products

that are damaged due to negligent use.

Service and Repairs

All repairs are made at GRAS International Support Center located in Denmark. Our Support Center is equipped with the newest test equipment and staffed with dedicated and highly skilled engineers. Upon request, we make cost estimates based on fixed repair categories. If a product covered by warranty is sent for service, it is repaired free of charge, unless the damage is the result of negligent use or other violations of the warranty.

CONDITIONING		
Frequency response (± 0.2 dB)	Hz	0.05 to 200 k
Output channel(s)		2
Output impedance	Ω	30
Direct coupling input to output		No
Linear mode		No
Type		Traditional power supply (LEMO)
Input channel(s), traditional power supply		2
Preamplifier supply	V	± 15
Polarization voltage	V	0 / 200
Overload indication		No
PC controlable		No
External filter option		No
Power amplifier overload detection		No
POWER SUPPLY		
Power supply, battery		4 x LR6 (AA)
Power supply, external	Vdc	4.5 to 24
Power consumption	mA	45
Battery life	h	30
Battery low indication		Yes
Fuse	mA	160 (slow)
Weight	g / oz	540.00 / 19.05

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.

Accessories

GRAS AB0002	Mains/line adapter
-------------	--------------------

GRAS Sound & Vibration reserves the right to change specifications and accessories without notice.

GRAS Worldwide

Subsidiaries and distributors in more
than 40 countries

GRAS SOUND & VIBRATION A/S
Skovlytoften 33
2840 Holte
Denmark
Tel: +45 4566 4046
gras@gras.dk

GRAS SOUND & VIBRATION USA
2234 East Enterprise Parkway
Twinsburg, OH 44087
United States
Tel: +1 330 425 1201
sales@gras.us

GRAS SOUND & VIBRATION UK
Building 115
Bedford Technology Park Thurleigh,
MK44 2YA Bedford
United Kingdom
Tel: +44 1234 639552
sales@gras.co.uk

GRAS SOUND & VIBRATION CHINA LTD.
Rm 1606, Kodak House II
No. 39 Healthy Street East North Point
Hong Kong
China
Tel: +852 2833 9987
sales@gras.com.cn



About GRAS Sound & Vibration

GRAS is a worldwide leader in the sound and vibration industry. We develop and manufacture state-of-the-art measurement microphones to industries where acoustic measuring accuracy and repeatability is of utmost importance in R&D, QA and production. This includes applications and solutions for customers within the fields of aerospace, automotive, audiology, and consumer electronics. GRAS microphones are designed to live up to the high quality, durability and accuracy that our customers have come to expect and trust.

GRAS Sound
& Vibration